# **DATA SHEET**



## BASIC EXPRESS PD 360° 08 IR 1C FM IP23 WH



## **Product description**

- Presence detector with 360° detection angle for recessed ceiling mounting
- Range of up to 8 m in diameter at a recommended installation height of 2.5 m
- 10 A high-performance relay
- Zero-cross switching for gentle switching
- Factory settings mean the device is ready for immediate use
- Easy to configure via remote control or using the ESY-Pen and ESY-App
- Offers special product features such as:
- Zero-cross switching
- Easy to configure, remotely control and document using the ESY-Pen and ESY-App

	<b>YEARS</b>
J	MANUFACTURER WARRANTY
	mannan

#### **Technical data**

### GENERAL

GENERAL			
Device category	Ceiling-mounted presence detector		
Included in delivery	*UNDEFINED TEXT*		
Product information	Mounting position: Keep a safe distance of 5 m from radio antennas (e.g. WiFi access points).		
User interface	IR remote control with "blue mode" technology, Push button input		
Remote controllable	$\checkmark$		
Conformity	CE, EAC, RoHS, WEEE		
Warranty	5 years		
ATTACHMENT			
Installation type	Recessed ceiling mounting		
Installation position	Ceiling		
Installation dimension	Installation denth: 57 mm. Ø 62 mm		

Installation position	Ceiling
Installation dimension	Installation depth: 57 mm, Ø 62 mm
Type of connection	Push terminal
Connectable wire cross section	0,75 – 2,5 mm <sup>2</sup>

HOUSING

Dimensions	Height/Depth 79 mm, Ø 79 mm	
Weight	82 g	
Material	UV-stabilised polycarbonate	
Protection type	IP23	
Permissible ambient temperature	-25 °C+50 °C	
Relative humidity	5 – 93 %, non-condensing	
Colour	white, similar to RAL 9010	

### ELECTRICAL VERSION

Control system	ON/OFF
Protection class	I

Nominal voltage	230 V AC / 50 Hz
In-rush current	78 A / 5 ms
Power consumption	0,4 W
SENSORS	
Detection angle	360°
Detection range diagonally	Ø8m
Detection range head-on	Ø5m
Detection range presence	Ø4m
Field of detection	up to 50 m <sup>2</sup>
Recommended installation height	2,5 m
Max. mounting height	5 m
Light measurement	mixed light
Level of brightness	10 – 2000 lx
CHANNELS (LIGHTING / HVAC)	
Push button input lighting	1
Number of parallel switchable detectors	10
Slave input	-
Mode	Semi-automatic, Fully automatic
Switching delay from "dark to light"	0 s
Switching delay from "light to dark"	30 s
Constant light control	-
Channel	<b>C1</b> Lighting
Function	Switching
Switching capacity	230 V/50 Hz
	2300 W/10 A (cos phi = 1) 1150 VA/5 A (cos phi = 0,5)
	400 W LED
Switch contact	make contact / non-floating



Frontal (B)

Presence area (C)


C<sup>●</sup> B↑ 360° Ø5m

Ø4m

## BASIC EXPRESS PD 360° 08 IR 1C FM IP23 WH

ltem number	GTIN					
B10431784	4015120431784					
witch-off delay time		15 s30 min (adjustable i	n steps)			
ccessories						
Product designation	I	ltem number	Product description			GTIN
Electrical accessorie	s					
FILTER 230 V		EP10426988	Filter for suppression of inducti	Filter for suppression of inductive loads, such as relays, contactors, fluorescent lamps and transformers		4015120426988
Protection						
BASKET GUARD ROUND	) LARGE	EM10425608	Basket guard for presence and motion detectors and smoke detectors, Ø 180 mm, height 90 mm		4015120425608	
Remote control						
ESY-Pen		EP10425356	ESY-Pen and ESY-App, two tools for every task: (1) Parameterisation, (2) remote control, (3) light measurement, (4) project management		4015120425356	
REMOTE CONTROL MD	i/PDi	EM10425509	IR remote control for presence detectors and motion detectors		4015120425509	
Dimension drawing	I			Field of detections	<b>Detection range</b>	
					Diagonally (A)	Ø 8 m
	Ø79 mm	Ø 62 mm				

#### Circuit diagram



57 mm

Standard with optional control via a closing button and parallel wiring of max. 8 devices.

## **DATA SHEET**



## BASIC EXPRESS PD 360° 08 IR 1C FM IP23 WH

Item number GTIN

EB10431784

4015120431784

#### **Detailed product description**

- Presence detectors with 360° detection angle for recessed ceiling mounting
- Range of up to 8 m in diameter at a recommended installation height of 2.5 m
- 10 A high-performance relay
- Zero-cross switching: Extension of the service life of the relay and illuminant with electronic ballasts (e.g. fluorescent luminaires, LEDs) through gentle zero-cross switching
- Factory settings mean the device is ready for immediate use
- Easy to configure via remote control or using the ESY-Pen and ESY-App
- Automatic light control
- Additional push button input
- Detection angle can be extended using parallel wiring