



[Click here to discover this product in 360°](#)

PRODUCT INFORMATION



Reference : GB-150-011



Protocols : 2 wires



Technologies : Mifare Plus, 868MHz

DESCRIPTION

The HF Easy Door Receiver access control system is designed for small residences. This system acts as a powerhouse and receiver at the same time. It was created to control 2 doors and manage up to 2000 users.

Easy Door Receiver is a product that can be used remotely from its installation site (Virtual Network mode) or on site (stand-alone mode).

To manage it remotely, an encoder and an Internet connection are required to control it from www.easydoorcontroller.com. Next:

1. Note the number of the controller installed (specified on the cover)
2. Register on www.easydoorcontroller.com
3. Program the badges using the encoder which stores one or more authorised door numbers inside the badge/remote control.

To remotely delete the authorisations on a badge or remote control, you just have to cancel the badge on the website www.easydoorcontroller.com and program a new one instead. When the new badge is used for the first time, the old one is blocked directly.

KEY CHARACTERISTICS

- Size (L X H X P) : 120 mm x 100 mm x 40 mm
- Remote programming with an encoder and an Internet connection
- Wiring: 2 wires / 100 m max. between the reader and the controller.
- Power supply: 12/24 Vac or Vcc
- NO/NC relay switch
- Time delay adjustable from 1 second to 99 seconds
- Pluggable terminals
- Operating temperature: -20°C to +60°C